

MIXER FOR A/V MODULATORS



ITEM		MIX/I	MIX/III	MIX/U
TV ANTENNA INPUT	MHz	5... 860	5... 860	5... 860
MODULATOR CHANNEL FILTER	Mhz	47... 68	47... 300	47... 860
TV DISTRIBUTION OUTPUT	Mhz	5... 860	5... 860	5... 860
ANT TV DISTR. TV ATTENUATION	dB	3,5	3,5	3,5
LNB/SAT RX ATTENUATION	dB	1	1	1
MIX MODULATOR ATTENUATION	dB	4	4	4
SAT/TV ISOLATION	dB	> 45	> 45	> 45
MODULATOR/SAT RX ISOLATION	dB	> 40	> 40	> 40
INVERTED ISOLATION	dB	> 16	> 30	> 25
RETURN LOSS	dB	> 12	> 12	> 12
DIMENSIONS	mm	56 x 46 x 27	56 x 46 x 27	56 x 46 x 27
COMPATIBILITY WITH CPS2		YES	YES	YES

The MIX series has been conceived specifically for our A/V modulators. They simplify the network realization combining several features in one single product.

